

Product data sheet

1-gang switch 16 AX / 400 V ~



Reference number

803 W

1-gang switch 16 AX / 400 V ~

with screw terminals for rigid and flexible wires up to 4 mm²

Switch can be illuminated in OFF-position with lamp ref.-no. 98 or 98-220 (230 V).

Notice!

Installation only by persons with relevant electrical knowledge and experience!*)

Use only with original JUNG product components approved for this article.

By inappropriate installation you endanger

- your own life,
- the life of the user of the electrical appliance.

By inappropriate installation you risk a high loss by damage, e.g. risk by fire.

You assume personal liability in cause of injury to persons or damage of appliances.

Please contact a skilled electrician!

*) Required technical knowledge for installation:

For installation, especially the following technical knowledge is required:

- the 5 important safety rules: disconnect from mains, secure against reconnecting, verify parts are free of voltage, ground and short-circuit, cover or block off adjacent live parts
- select adequate tools, measuring devices and personal protective equipment
- evaluate measuring results
- selection of the electrical installation material to secure switch-off conditions
- IP protection levels
- installation of the electrical installation material
- type of electric power grid (TN system, IT system, TT system) and the resultant connection terms (common grounding, protective ground, required additional action etc.)

Rocker with symbols I 0

Version:

3-pole, 1-way

Power SBL (self-ballasted lamps):

max. 200 W

Material:

thermoplastic



Degree of protection IP44 is ensured.