

# Product data sheet

## Rotary blind switch/push-button



### Reference number

834.20 W

### Rotary blind switch/push-button 10 A / 250 V ~

#### Up – Stop – Down

with inscription field 9 x 50 mm

with screw terminals for rigid and flexible wires up to 2.5 mm<sup>2</sup>

Can be converted into rotary push-button by means of locking piece (included).

A pre-travel prevents a quick change of direction.

Inscription fields may be customised using our GRAPHIC TOOL ([jung.group/gt](http://jung.group/gt)).

#### Notice!

**Installation only by persons with relevant electrical knowledge and experience!\*)**

**Use only with original JUNG product components approved for this article.**

By inappropriate installation you endanger

- your own life,
- the life of the user of the electrical appliance.

By inappropriate installation you risk a high loss by damage, e.g. risk by fire.

You assume personal liability in cause of injury to persons or damage of appliances.

**Please contact a skilled electrician!**

**\*) Required technical knowledge for installation:**

For installation, especially the following technical knowledge is required:

- the 5 important safety rules: disconnect from mains, secure against reconnecting, verify parts are free of voltage, ground and short-circuit, cover or block off adjacent live parts
- select adequate tools, measuring devices and personal protective equipment
- evaluate measuring results
- selection of the electrical installation material to secure switch-off conditions
- IP protection levels
- installation of the electrical installation material
- type of electric power grid (TN system, IT system, TT system) and the resultant connection terms (common grounding, protective ground, required additional action etc.)

#### Version:

2-pole (2 motors)

#### Material:

thermoplastic

**IP** Degree of protection IP44 is ensured.