

Product data sheet

SCHUKO® socket



Reference number

LC 1521 236

SCHUKO® socket 16 A / 250 V ~

with screw terminals for rigid and flexible wires up to 2.5 mm²

without claws: ref.-no. with additional "N", e.g.: ..1521 N..

Supporting frame, claws and claw screws are integrated into the earth protection.

Notice!

Installation only by persons with relevant electrical knowledge and experience!*)

Use only with original JUNG product components approved for this article.

By inappropriate installation you endanger

- your own life,
- the life of the user of the electrical appliance.

By inappropriate installation you risk a high loss by damage, e.g. risk by fire.

You assume personal liability in cause of injury to persons or damage of appliances.

Please contact a skilled electrician!

*) Required technical knowledge for installation:

For installation, especially the following technical knowledge is required:

- the 5 important safety rules: disconnect from mains, secure against reconnecting, verify parts are free of voltage, ground and short-circuit, cover or block off adjacent live parts
- select adequate tools, measuring devices and personal protective equipment
- evaluate measuring results
- selection of the electrical installation material to secure switch-off conditions
- IP protection levels
- installation of the electrical installation material
- type of electric power grid (TN system, IT system, TT system) and the resultant connection terms (common grounding, protective ground, required additional action etc.)

matt lacquered

Colour:

terre sienne brique

Material:

duroplastic lacquered



Individual colour printing possible